



RLY34

30/40 Amp Relay



- Bosch-Style 5-Pin SPDT Relay
- 30A Max Current, 40A Surge Current
- Weather Resistant design
- Transient Protection diode included on coil
- Includes standard N/O and N/C Contacts
- Features industry standard terminal labels (30, 85, 86, 87 and 87a)
- Compatible with Wirez RLYH34 Wired Relay Socket

Sold in bulk packs of 10 under part number RLY34-10



With the electronic circuits in vehicles becoming more and more fragile and sensitive, Wirez has chosen to include a Transient Voltage Protection diode in the RLY34. This diode shunts the current spike that is generated when the coil opens and prevents voltage spikes at the controlling equipment. This increases reliability and longevity of the controlling device.

With the diode integrated into the relay, it is necessary to be conscious of how power is applied to the coil of the relay. **+12V MUST be on Terminal 85 and Ground on Terminal 86. Failure to comply will result in damage to the relay.**

